




- ダーリントン・トランジスタ2個内蔵
- フリーホイール・ダイオード付
- 絶縁形
- 直流電流増幅率は70以上(定格電流にて)


■等価回路




注1. 1トランジスタ当たり。 注2. AC, 1分間。 注3. #印は V_{CE0} (I_C の単位はmA)。

型 名	最 大 定 格										電 氣 的 特 性										
	V _{CE0} (V)	V _{CE0 (SUS)} V _{CE0} # (V)	V _{EB0} (V)	I _C (A)	I _{CP} (ImS) (A)	I _B (A)	I _F (A)	P _C		T _i (°C)	T _{stg} (°C)	V _{iso} (V)	I _{CE0}		V _{CE0 (SUS)}		h _{FE}				
								(W)	Total (W)				最大 (mA)	V _{CE} (V)	最大 (mA)	V _{EB} (V)	V _{CE0 (SUS)}		最小 (V)	I _C (A)	
																	(V)(注3)	I _C (A)			
1D200A-020	300	300 #	6	200	400	8.0		800		150	-40~125		1.0	300	200	6	250	1.0	100	5	200
1D500A-030	400	400 #	10	500	1000	20		2500		150	-40~125		1.0	400	800	10	300	1.0	500	2	500
1D1200A-120	1200	1200 #	10	200	400	12	200	1400		150	-40~125	2500	2.0	1200	400	10	1200 #	2	70	5	200
1D1200A-140	1400	1400 #	10	200	400	12	200	1400		150	-40~125	2500	2.0	1200	400	10	1400 #	30	70	5	200
1D1200Z-100	1000	1000 #	10	200	400	10	200	1400		150	-40~125	2500	4.0	1000	800	10	1000 #	4	100	5	200
1D1200Z-120	1200	1200 #	10	200	400	12	200	1400		150	-40~125	2500	4.0	1200	800	10	1200 #	4	100	5	200
1D1240A-055	600	550	6	240	480	12	240	1000		150	-40~125	2500	2.0	600	600	6	550	2.0	70	5	240
1D1300A-120	1200	1200 #	10	300	600	16	300	2000		150	-40~125	2500	2.0	1200	400	10	1200 #	2	70	5	300
1D1300A-140	1400	1400 #	10	300	600	16	300	2000		150	-40~125	2500	2.0	1200	400	10	1400 #	30	70	5	300
1D1300D-100	1000	1000 #	10	300	600	16	300	2000		150	-40~125	2500	1.0	1000	800	10	800	5.0	100	5	300
1D1300Z-100	1000	1000 #	10	300	600	16	300	2000		150	-40~125	2500	4.0	1000	800	10	1000 #	4	100	5	300
1D1300Z-120	1200	1200 #	10	300	600	16	300	2000		150	-40~125	2500	4.0	1200	800	10	1200 #	4	100	5	300
1D1400A-120	1200	1200 #	10	400	800	32		3120		150	-40~125	2500	4.0	1200	600	10	1200 #	4	100	5	400
1D1400D-100	1000	800	10	400	800	16	400	2400		150	-40~125	2500	1.0	1000	800	10	800	5.0	70	5	400
1D1480A-055	600	550	6	480	960	16	480	2000		150	-40~125	2500	4.0	600	800	6	550	5.0	70	5	480
ET1275	1000	1000 #	6	15	30	3.0		120		150	-40~125	2500	1.0	1000	200	6	700	1.0	20	5	12
ETG81-050A	600	450	6	30	60	2.0	30	200		150	-40~125	2000	1.0	600	150	6	450	1.0	100	5	30
ETK81-050	600	450	6	50	100	3.0	50	300		150	-40~125	2000	1.0	600	200	6	450	1.0	100	5	50
ETK85-050	600	450 #	6	75	150	4.5	75	350		150	-40~125	2000	1.0	600	200	6	450	1.0	70	5	75
ETL81-050	600	500	6	100	200	6.0	100	600		150	-40~125	2500	1.0	600	300	6	500	1.0	100	5	100


FD-1




FD-2




FD-3




FD-4




FD-5




FD-6




FD-7




FD-8



FD-9




FD-10




FD-11

FD-12


H-1




H-2




H-3




H-4




H-5




H-6




H-7




H-8A




H-8B



H-9A




H-9B




- ① アノード
- ② カソード
- ③ ゲート

H-10




M12P1.5③

H-11




M12P1.5

H-12




M20P1.5

H-13




M24P1.5②

H-14



Unit in mm (inch)


H-15




Cathode auxiliary terminal
Gate terminal

Unit in mm (inch)


H-16




H-17




H-18




H-19




H-20




H-21




H-22




H-23




H-24



H-25




H-26




Type	Direction of polarity
CA12	

H-27




Type	Direction of polarity
CF11V	

H-28




Note: The thickness is a dimension in press at the rated mounting force.

H-29




Note : The thickness is a dimension in press at the rated mounting force.

H-30





Note : The thickness is a dimension in press at the rated mounting force.

HT-1




Unit in mm (inch)


HT-2




HT-3



HT-4




HT-5




《寸法図単位：mm》


M-1




M-2




M-3




M-4




M-5




M-6




M-7




M-8




M-9




M-10




M-11




M-12




M-13




M-14




M-15




M-16




M-17




M-18




M-19




M-20




M-21




M-22




M-23




M-24




M-25




M-26




M-27




M-28




M-29




M-30




M-31




M-32




M-33




M-34




MT-1




MT-2




MT-3




MT-4




MT-5




MT-6




MT-7




MT-8




MT-9




MT-10




MT-11




MT-12




MT-13




MT-14




MT-15




MT-16




MT-17




MT-18




MT-19




MT-20




MT-21




MT-22



MT-23




MT-24



- ① T1 端子
- ② T2 端子
- ③ ゲート端子
- ④ T2 端子


TO - 3P

N-1




電極接続
① カソード
② ゲート
③ アノード

N-2




電極接続
① ヤート
② アノード
③ カソード

N-3




電極接続
① カソード
② アノード
③ ゲート

N-4




電極接続
① カソード
② アノード
③ ゲート

N-5




N-6




電極接続
① カソード
② アノード
③ ゲート

N-7




N-8



電極接続
① カソード
② アノード
③ ゲート
④ フィン(アノード)

N-9




電極接続

K : カソード

A : アノード

G : ゲート

NA-1




電極接続

1. ゲート
2. アノード
3. カソード

JEDEC: TO-92

NA-2




電極接続

1. カソード
2. アノード
3. ゲート


JEDEC: TO-202AA

NI-1




NI-2

29RD




NI-3

39RC
59RC
39RF
59RF




NI-4

68RP, 88RP, 108RP, 68RS,
88RS, 78RT, 88RLD, 88RLE,
88RLF, 88RLG, 88RLH, 108RLE




NI-5

158RP, 208RP, 128RS, 178RS,
158RT, 178RLD, 178RLE,
178RLF, 178RLG, 178RLH,
208RLE




NI-6

308RP, 408RP, 508RP, 278RS,
358RS, 258RT, 258RLD, 258RLG,
258RLH, 308RLE, 308RLF,
358RLE




NI-7

89RW $\frac{1}{2}$ L
129RW $\frac{1}{2}$ L




NI-8

89RW
129RW




NI-16

503PLF
503PLH




NI-17

3003PA




NI-18

353PGA「E




NI-19

603PGA, 603PGA「A, 803PGA




NI-20

603PGA「E




NI-21

1001PGB「E




NI-22

1201PGA, 1201PGA「A, 1401PGA




NI-23

1201PGA「E



NI-24


2001PGB^r JE



NI-25


NI-26

NT-1




電線接続
① T₁
② ゲート
③ T₂

NT-2




電線接続
① T₁
② ゲート
③ T₂

NT-3




電線接続
① T₁
② T₂
③ ゲート

NT-4




電線接続
① T₁
② T₂
③ G

NT-5




電線接続
トリアック
① T₁
② T₂
③ ゲート
④ 2K

NT-6




電線接続
トリアック
① T₁
② T₂
③ ゲート
④ 2K

NT-7




NT-8




電線接続
① T₁
② T₂
③ G
④ ツイン(T₂)


S-1




ST-1




SA-1




SA-2




SA-3




SA-4




SA-5




SA-6




SA-7




SA-8




SA-9




SA-10




SA-11



SA-12




SAT-1




T1端子: ファストン 250 (T=6.35, t=0.8, φ=1.65)
 T2端子: ファストン 250 (T=6.35, t=0.8, φ=1.65)
 G 端子: ファストン 187 (T=4.75, t=0.5, φ=1.3)

SAT-2




スペース留め


SAT-3




SAT-4




SAT-5




SAT-6




SAT-7




SAT-8




SAT-9




SAT-10




SAT-11




SY-1(1096A)




SY-2(1151)




SY-3(1104)



SY-4(1150)




1097A




G: Gate


1102




1141




1142




1144



1155




1192A




G: Gate


T-1 (13-5A1A)




T-2 (13-8A1A)




T-3 (13-8C1A)




T-4 (13-10A1A)




T-5 (13-10B1A)




T-6 (13-11D1A)




T-7 (13-13A1A)




T-8 (13-13B1A)




T-17 (13-42A1A)




T-18 (13-45D1A)




T-19 (13-52B1A)




T-20 (13-52C1A)




T-21 (13-60A1A)




T-22 (13-70C1A)




T-23 (13-78A1A)




T-24 (13-100C1A)




T-25 (13-120A2A)




T-26 (13-150A1A)




T-27 (13-37A1A)




T-28 (13-45E1A)




T-29 (13-51A1A)




T-30 (13-57A1A)




T-31 (13-100E1A)



T-32 (13-60E3A)




T-33 (13-78B1A)




- ① カソード
② アノード
③ ゲート

T-34 (13-66A1A)




- ① カソード
② アノード
③ ゲート

T-35 (13-100D1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-36 (13-120E1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-37 (13-120A1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-38 (13-120C1A)




- ① カソード
② アノード
③ ゲート

T-39 (13-80B1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-40 (13-28A1A)




1. カソード
2. アノード
3. ゲート


T-41 (13-28A2A)




T-42 (13-45F1A)




T-43 (13-60E2A)




T-44 (13-36A1A)




T-45 (13-51B1A)




T-46 (13-36B1A)




T-47 (13-60E1A)



T-48 (13-93C1A)




T-49 (13-75A1A)




- 1 ①-(1) カソード
1 ①-(2) カソード (黒)
2 アノード
3 ゲート (白)

T-50 (13-10A3A)




- 1 カソード
2 アノード
3 ゲート

T-51 (13-10D1A)




- 1 カソード
2 アノード
3 ゲート

T-52 (13-10D2A)




- 1 カソード
2 アノード
3 ゲート

T-53 (13-10E1B)




- 1 カソード
2 アノード
3 ゲート

T-54 (13-10F1B)




- 1 カソード
2 アノード
3 ゲート

T-55 (13-5A1D)




- 1 カソード
2 ゲート
3 アノード

T-56 (13-13C1A)




- 1 カソード
2 アノード
3 ゲート


TT-1




TT-2




TT-3




TT-4




TT-5




TT-6




TT-7



TT-8




TT-9




1. ゲート
2. T₁
3. T₂ (ケース)

TT-10




1. ゲート
2. T₁
3. T₂ (ケース)

TT-11



1. ゲート (ファストン端子 #187)
2. T₁ (" #250)
3. T₂ (" #250)


TT-12



ゲート端子詳細


- ① ゲート (ファストン端子 #187)
- ② T₁ (" #250)
- ③ T₂ (" #250)

TT-13




- 1, 2: T₂
- 3: GATE
- 4: T₁

TT-14




- 1, 2: T₂
- 3: GATE
- 4: T₁

TT-15 (13-14A1B)




1. ゲート
2. T₁
- T₂ (ケース)

TT-16 (13-16A1A)




1. T₁
2. T₂
3. ゲート


TS-1




TS-2




TS-3




TS-4




TS-5








TS-6




TS-7







S-94B2A




S-94D1A




S-95A1A




S-95B1A




S-98B1B




S-108A2A




S-108B1A




S-108B1B




S-108B1C




S-108B2A




S-108B2B




2-22B1A




2-27A4A




2-33C1A




2-33D1A




2-33F1A




2-37A1A




2-48A3A




2-48A3B




2-48A4A




2-64A2A




2-64A2B




2-68A2A




2-68B2A




2-68C1A




2-68D2A




2-72A3A




2-80A1A




2-80B1A




2-80C1A




2-80D2A




2-94A2A




2-94B1A




2-94C2A




2-94C3A




2-108B1A




2-109A3A




2-109A4A



2-109B3A




2-109B4A




BBT-II

BBTII
1D200A-020




BBT-III

BBTIII
ETN31-055
ETN36-030
ETN36-030
ETN35-030




BBT-III







BBTIII
ETN01-055
ET1257




BBT-IV

BBTIV
1D500A-030







M-107




M-116




M-201




M-202




M-203




M-204




M-205




M-206




M-207




M-208




M-209




M-210




M-211



M-212




M-213




M-214


M-215




M-216




M-217




M-218




M-601




M-602




M-603




M-604




M-605




M-606




M-1A1A




M-2A1A




M-2B1A




M-2B2A




M-2C2A




M-2D4A




M-2E6A




M-2F6A




M-2G6A




M-3A1A




M-3B1A




M-3B1B




M-3C1A




M-3D6A




M-3E6A




M-4A1A




M-4A2A




M-4A1B




M-4A2B




M-4B2A




M-5A1A




M-5A1B




M-5A2A




M-5B2A




M-5C2A




M-5D2A




M-6A1A




M-7A1A




M-7B1A




M-8A1A




M-8A1B




M-8A2A




M-8A2B




M-8B2A




M-9A1A




M-9A2A




M-9B1A




M-9C2A




M-1A1B




M-1A1C




M-2E6B




M-2E6C




M-10A2A




M-10A2B




M-11A2A




M-12A6A




M-12B6A




M-12B6B




M-4A2D




M-4A2E




M-4C2A




M-4C2B




M-9B1C




M-9D2A






M-9D2B



M-10A2C




H-101




Weight :480g



H-201





H-202




LF-J




LF-K




U-1




U-2




U-3



U-4




U-5




1. BASE 1
2. EMITTER
3. BASE 2 (CASE)

U-6



1. BASE (2)
2. EMITTER
3. BASE (1)

U-7



U-8

