


注1. $I_C = 1\text{ A}$, $V_{EB} = 2\text{ V}$, #印は V_{CEX} ($V_{EB} = 2\text{ V}$)

注2. 60Hz、単相半波1サイクル波高値。


注3. $T_c = 25^\circ\text{C}$.

注4. AC, 1分間。


[illegible]

[illegible]


FD-1




FD-2




FD-3




FD-4




FD-5




FD-6




FD-7




FD-8




H-1




H-2




H-3




H-4




H-5




H-6




H-7




H-8A




H-8B



H-9A




H-9B




- ① アノード
② カソード
③ ゲート


H-10




H-11




H-12



H-13




H-14




Unit in mm (inch)

H-15




Unit in mm (inch)


H-16




H-17




H-18




H-19




H-20




H-21




H-22




H-23




H-24



H-25




H-26



Type	Direction of polarity
CA12	


H-27



Type	Direction of polarity
CF11V	


(注) CC11V: 400 $\pm$ 10
CF11V: 250 $\pm$ 10

H-28




Note: The thickness is a dimension in press at the rated mounting force.

H-29




Note : The thickness is a dimension in press at the rated mounting force. Weight: 870(g)

H-30





Note : The thickness is a dimension in press at the rated mounting force. Weight: 1,460(g)

HT-1




Unit in mm (inch)


HT-2




HT-3



HT-4




HT-5




《寸法図単位：mm》


M-1




M-2




M-3




M-4




M-5




M-6




M-7




M-8




M-9




M-10




M-11




M-12




M-13




M-14




M-15




M-16




M-17




M-18




M-19




M-20




M-21




M-22




M-23




M-24




M-25




M-26




M-27




M-28




M-29




M-30




M-31




M-32




M-33




M-34




MT-1




MT-2




MT-3




MT-4




MT-5




MT-6




MT-7




MT-8




MT-9




MT-10




MT-11




MT-12




MT-13




MT-14




MT-15




MT-16




MT-17




MT-18




MT-19




MT-20




MT-21




MT-22



MT-23




MT-24



TO - 3P

- ① T1 端子
- ② T2 端子
- ③ ゲート 端子
- ④ T2 端子


N-1



電極接続

- ① カソード
- ② ゲート
- ③ アノード


N-2



電極接続

- ① ヤート
- ② アノード
- ③ カソード


N-3



電極接続

- ① カソード
- ② アノード
- ③ ゲート


N-4




電極接続

- ① カソード
- ② アノード
- ③ ゲート

N-5




N-6




電極接続

- ① カソード
- ② アノード
- ③ ゲート

N-7




N-8



電極接続

- ① カソード
- ② アノード
- ③ ゲート
- ④ フィン(アノード)

N-9




電極接続

K : カソード

A : アノード

G : ゲート

NA-1




電極接続

1. ゲート
2. アノード
3. カソード

JEDEC: TO-92

NA-2




電極接続

1. カソード
2. アノード
3. ゲート

JEDEC: TO-202AA


NI-16

503PLF
503PLH




NI-17

3003PA




NI-18

353PGA「E




NI-19

603PGA, 603PGA「A, 803PGA




NI-20

603PGA「E




NI-21

1001PGB「E




NI-22

1201PGA, 1201PGA「A, 1401PGA




NI-23

1201PGA「E



NI-24


2001PGB^r JE



NI-25


NI-26

NT-1




電線接続
① T₁
② ゲート
③ T₂

NT-2




電線接続
① T₁
② ゲート
③ T₂

NT-3




電線接続
① T₁
② T₂
③ ゲート

NT-4




電線接続
① T₁
② T₂
③ G

NT-5




電線接続
トライアック
① T₁
② T₂
③ ゲート
④ 2K

NT-6




電線接続
トライアック
① T₁
② T₂
③ ゲート
④ 2K

NT-7




NT-8




電線接続
① T₁
② T₂
③ G
④ T₁ (T₂)


SA-1




SA-2




SA-3




SA-4




SA-5




SA-6




SA-7




SA-8




SA-9




SA-10




SA-11



SA-12




SAT-1




T1端子:ファストン250($T=6.35$, $t=0.8$, $\phi=1.65$)
T2端子:ファストン250($T=6.35$, $t=0.8$, $\phi=1.65$)
G端子:ファストン187($T=4.75$, $t=0.5$, $\phi=1.3$)


SAT-2




SAT-3




SAT-4




SAT-5




SAT-6




SAT-7




SAT-8




SAT-9.




SAT-10




SAT-11




SY-1(1096A)




SY-2(1151)




SY-3(1104)



SY-4(1150)




1097A




G: Gate


1102




1141




1142




1144



1155




1192A




G: Gate


T-1 (13-5A1A)




T-2 (13-8A1A)




T-3 (13-8C1A)




T-4 (13-10A1A)




T-5 (13-10B1A)




T-6 (13-11D1A)




T-7 (13-13A1A)




T-8 (13-13B1A)




T-17 (13-42A1A)




T-18 (13-45D1A)




T-19 (13-52B1A)




T-20 (13-52C1A)




T-21 (13-60A1A)




T-22 (13-70C1A)











T-23 (13-78A1A)




T-24 (13-100C1A)




T-25 (13-120A2A)**T-26** (13-150A1A)**T-27** (13-37A1A)**T-28** (13-45E1A)**T-29** (13-51A1A)**T-30** (13-57A1A)**T-31** (13-100E1A)**T-32** (13-60E3A)

T-33 (13-78B1A)




- ① カソード
② アノード
③ ゲート

T-34 (13-66A1A)




- ① カソード
② アノード
③ ゲート

T-35 (13-100D1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-36 (13-120E1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-37 (13-120A1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-38 (13-120C1A)




- ① カソード
② アノード
③ ゲート

T-39 (13-80B1A)




- ①-(1) カソード
①-(2) カソード(黒)
② アノード
③ ゲート(白)

T-40 (13-28A1A)




1. カソード
2. アノード
3. ゲート


T-41 (13-28A2A)




T-42 (13-45F1A)




T-43 (13-60E2A)




T-44 (13-36A1A)




T-45 (13-51B1A)




T-46 (13-36B1A)




T-47 (13-60E1A)



T-48 (13-93C1A)




T-49 (13-75A1A)




- 1 ①-(1) カソード
1 ①-(2) カソード (黒)
2 アノード
3 ゲート (白)

T-50 (13-10A3A)




- 1 カソード
2 アノード
3 ゲート

T-51 (13-10D1A)




- 1 カソード
2 アノード
3 ゲート

T-52 (13-10D2A)




- 1 カソード
2 アノード
3 ゲート

T-53 (13-10E1B)




- 1 カソード
2 アノード
3 ゲート

T-54 (13-10F1B)




- 1 カソード
2 アノード
3 ゲート

T-55 (13-5A1D)




- 1 カソード
2 ゲート
3 アノード

T-56 (13-13C1A)




- 1 カソード
2 アノード
3 ゲート


T-57 (12-16C1A)




T-58 (13-10H1B)




T-59 (13-120A1A)




T-60




T-61 (13-5B1A)




T-62 (13-10H1A)




T-63 (13-16A1B)




TT-1




TT-2




TT-3




TT-4




TT-5




TT-6




TT-7



TT-8




TT-9




1. ゲート
2. T₁
3. T₂ (ケース)

TT-10




1. ゲート
2. T₁
3. T₂ (ケース)

TT-11



1. ゲート (ファストン端子 #187)
2. T₁ (" #250)
3. T₂ (" #250)


TT-12



ゲート端子詳細


- ① ゲート (ファストン端子 #187)
- ② T₁ (" #250)
- ③ T₂ (" #250)

TT-13




- 1, 2: T₂
- 3: GATE
- 4: T₁

TT-14




- 1, 2: T₂
- 3: GATE
- 4: T₁

TT-15 (13-14A1B)




1. ゲート
2. T₁
- T₂ (ケース)

TT-16 (13-16A1A)




1. T₁
2. T₂
3. ゲート


TS-1




TS-2




TS-3




TS-4




TS-5








TS-6




TS-7







S-94B2A




S-94D1A




S-95A1A




S-95B1A




S-98B1B




S-108A2A




S-108B1A




S-108B1B




S-108B1C




S-108B2A




S-108B2B




2-22B1A




2-27A4A




2-33C1A




2-33D1A




2-33F1A




2-37A1A




2-48A3A




2-48A3B




2-48A4A




2-64A2A




2-64A2B




2-68A2A




2-80C1A




2-80D2A




2-94A2A




2-94B1A




2-94C2A




2-94C3A




2-108B1A




2-109A3A




2-109A4A



2-109B3A




2-109B4A




BBT-II

BBTII
1D200A-020




BBT-III

BBTIII
ETN31-055
ETN36-030
ETN36-030
ETN35-030




BBT-III







BBTIII
ETN01-055
ET1257




BBT-IV

BBTIV
1D500A-030







M-107




M-116




M-201




M-202




M-203




M-204




M-205




M-206




M-207




M-208




M-209




M-210




M-211



M-212




M-213




M-214


M-215




M-216




M-217




M-218




M-601




M-602




M-603




M-604




M-605




M-606




M-607




M-608




M-609




M-610




M-616




M-2E6A




M-2F6A




M-2G6A




M-3A1A




M-3B1A




M-3B1B




M-3C1A




M-3D6A




M-3E6A




M-4A1A




M-4A2A




M-4A1B




M-4A2B




M-4B2A




M-5A1A




M-5A1B




M-5A2A




M-5B2A




M-5C2A




M-5D2A




M-6A1A




M-7A1A




M-7B1A




M-8A1A




M-8A1B




M-8A2A




M-8A2B




M-8B2A




M-9A1A




M-9A2A




M-9B1A




M-9C2A




M-1A1B




M-1A1C




M-2E6B




M-2E6C




M-10A2A




M-10A2B




M-11A2A




M-12A6A




M-12B6A




M-12B6B




M-4A2D




M-4A2E




M-4C2A




M-4C2B




M-9B1C




M-9D2A






M-9D2B



M-10A2C




H-101




Weight :480g

TERMINALS



H-201





H-202




LF-J




LF-K




U-1




U-2




U-3



U-4




U-5




1. BASE 1
2. EMITTER
3. BASE 2 (CASE)

U-6



1. BASE (2)
2. EMITTER
3. BASE (1)

U-7



U-8

