

NJM 4556 M	OP-IC	=NJM 4556D: SMD	8-MDIP	-	
NJM 4556 S	OP-IC	=NJM 4556D: Fig. →	9-SIP	-	
NJM 4558 D	OP-IC	Dual, Serie 158, 1V/μs, 3MHz, -20...+75°	8-DIP	4558/8-D	8-DIP
NJM 4558 F	OP-IC	=NJM 4558D: SMD	8-FLP	-	
NJM 4558 L	OP-IC	=NJM 4558D: Fig. →	8-SIP	-	
NJM 4558 M	OP-IC	=NJM 4558D: SMD	8-MDIP	-	
NJM 4558 S	OP-IC	=NJM 4558D: Fig. →	9-SIP	-	
NJM 4558 T	OP-IC	=NJM 4558D: Fig. →	TO-99	-	
NJM 4559 D,M,S,T	OP-IC	=NJM 4558D, M, S, T: 2V/μs, 6MHz	-	-	
NJM 4560 D	OP-IC	Dual, ±18V, 4V/μs, 10MHz, -20...+75°	8-DIP	-	
NJM 4560 L	OP-IC	=NJM 4560D: Fig. →	8-SIP	-	
NJM 4560 M	OP-IC	=NJM 4560D: SMD	8-MDIP	-	
NJM 4560 S	OP-IC	=NJM 4560D: Fig. →	9-SIP	-	
NJM 4560 T	OP-IC	=NJM 4560D: Fig. →	TO-99	-	
NJM 5532 D	OP-IC	Dual, lo-noise, ±22V, 8V/μs, -20...+75°	8-DIP	→NE 5532...	
NJM 7805(A)	Z-IC	+5V, 10%(A=5%), 1A	17b	7805/TO-220	17b
NJM 7806(A)	Z-IC	+6V, 10%(A=5%), 1A	17b	7806/TO-220	17b
NJM 7808(A)	Z-IC	+8V, 10%(A=5%), 1A	17b	7808/TO-220	17b
NJM 7809(A)	Z-IC	+9V, 10%(A=5%), 1A	17b	7809/TO-220	17b
NJM 7812(A)	Z-IC	+12V, 10%(A=5%), 1A	17b	7812/TO-220	17b
NJM 7815(A)	Z-IC	+15V, 10%(A=5%), 1A	17b	7815/TO-220	17b
NJM 7818(A)	Z-IC	+18V, 10%(A=5%), 1A	17b	7818/TO-220	17b
NJM 7820(A)	Z-IC	+20V, 10%(A=5%), 1A	17b	7820/TO-220	17b
NJM 7824(A)	Z-IC	+24V, 10%(A=5%), 1A	17b	7824/TO-220	17b
NJM 78xx F(A)	Z-IC	=NJM 7805...7824(A): Iso	17b	78xx/IsoTO-220	17b
NJM 7905(A)	Z-IC	-5V, 10%(A=5%), 1A	17c	7905/TO-220	17c
NJM 7906(A)	Z-IC	-6V, 10%(A=5%), 1A	17c	-	
NJM 7908(A)	Z-IC	-8V, 10%(A=5%), 1A	17c	-	
NJM 7909(A)	Z-IC	-9V, 10%(A=5%), 1A	17c	-	
NJM 7912(A)	Z-IC	-12V, 10%(A=5%), 1A	17c	7912/TO-220	17c
NJM 7915(A)	Z-IC	-15V, 10%(A=5%), 1A	17c	7915/TO-220	17c
NJM 7918(A)	Z-IC	-18V, 10%(A=5%), 1A	17c	-	
NJM 7924(A)	Z-IC	-24V, 10%(A=5%), 1A	17c	-	
NJM 79xx F(A)	Z-IC	=NJM 7905...7924(A): Iso	17c	(79xx/TO-220)	17c

3

NK....NZ

NL 3 T1	PUT	→2N6027			
NM	Ge-Di	=AA 133		AA 133	31a
NM 400	Si-N	TV-VA, 170V, 2A, 30W, >10MHz	22a	2SD1138	17j
NPS....	Si-N/P	→MPS....	7	→MPS....	
NR-001 E	Si-N	=BC 548	7e	BC 546	7a
NR 041 E	Si-N	Uni-ra, 20V, 0.03A, 0.6W	7e	BC 550	7a
NR 041 F	Si-N	=NR 041E:	7c	BC 550	7a
NR 041 H	Si-N	=NR 041E:	7a	BC 550	7a
NR-071 E	Si-N	=BC 548	7e	BC 546	7a
NR 421 D....	Si-N	FM/VHF, 700MHz	7f	BF 198	7d
NR 421 F....	Si-N	=NR 421D:	7c	BF 198	7d
NR 431 E....	Si-N	AM/FM, 600MHz	7e	BF 198	7d
NR 431 F....	Si-N	=NR 431E:	7c	BF 198	7d
NR 431 H....	Si-N	=NR 431E:	7a	BF 198	7d
NR 461 E....	Si-N	AM/FM-ZF, 300MHz	7e	BF 255	7d
NR 461 F....	Si-N	=NR 461E:	7c	BF 255	7d
NR 461 H....	Si-N	=NR 461E:	7a	BF 255	7d
NR 601 E	Si-P	=BC 328	7e	BC 327	7a